

Your remote is already paired with your power base. Follow the below instructions for replacement remote pairing or pairing to multiple bases.

### A. Remote Pairing without Pairing Button

#### STEP 1

Place batteries into the remote control (3 x AAA batteries).

#### STEP 2

Ensure the power base is not plugged into an outlet. Have the plug and remote ready on hand.

#### STEP 3

Plug the control box into an outlet to start the pairing process. Pairing mode lasts for the first 5 seconds once plugged in.

**NOTE:** The control box emits a clicking sound during the 5 seconds of pairing mode.

#### STEP 4

Press and hold any button on the remote control to pair.

#### STEP 5

Test and verify the remote is correctly paired by activating functions of the power base. You have now completed the pairing process.

**NOTE:** To restart pairing mode - unplug the control box, wait 5 seconds, and plug in again into an outlet.

### B. Remote Pairing with Pairing Button

#### STEP 1

Place batteries into the remote control (3 x AAA batteries).

#### STEP 2

Ensure the power base is plugged into a functioning outlet.

#### STEP 3

Press and hold the pairing button on the control box until the indication light blinks.

**NOTE:** If a new signal is not received it will reset itself to normal mode in 30 seconds.

#### STEP 4

Press any button on the remote control. When the control box light turns solid, the remote should be successfully paired.

#### STEP 5

Test and verify the remote is correctly paired by activating functions of the power base. You have now completed the pairing process.

**Register Online.** For easy registration of your warranty visit <https://reverie.com/register-your-warranty>

Please prepare a digital copy of your proof of purchase (invoice or sales receipt) when registering online. You may be required to provide the Serial Number for registration, you can find it on the Law Tags attached to the base.

Manufactured by Reverie® For Warranty and Service:

1-800-973-8374

customerservice@reverie.com

Please have your receipt ready and available.

Thank you and enjoy your power base.

[www.reverie.com](http://www.reverie.com)

**MULTIPLE BASES:** If you want two sides to move in sync when using one remote (recommended for Split King/Cal King units) you can pair to both sides. Follow the steps in process A and/or B for each base you have.

Control Box without Pairing Button



Control Boxes with Pairing Button

